

## DIGITAL MULTIMETER MODEL : DM – 97

### Features:

- 3¾ Digital Multimeter
- 4000 Counts Large LCD Display with Auto/Manual Range
- No Power-OFF under natural operation
- Data Hold, Max. / Min. Value Hold
- Capacitance, Frequency / Duty Cycle, Temperature and Transistor Test



### Technical Data :

Basic Functions	Range	Basic Accuracy
DC Voltage	0.1mV ~ 1000V	± (0.5% + 4 digit)
AC Voltage	0.1mV ~ 750V	± (0.8% + 6 digit)
DC Current	0.1uA ~ 20A	± (1.0% + 5 digit)
AC Current	0.1uA ~ 20A	± (1.5% + 5 digit)
Resistance	0.1~ 40MΩ	± (0.8% + 2 digit)
Capacitance	10pF ~ 200uF	± (3.5% + 8 digit)
Frequency	0.1Hz ~ 30MHz	± (0.5% + 4 digit)
Celsius	-40oC~1000°C	± (0.8% + 4 digit)
hhFE (NPN or PNP)	0 ~ 1000	

### Special Function :

Diode test	✓	Function Protection	✓
Transistor testing	✓	Input impedance	10MΩ
Continuity Buzzer	Lower 30 +10	Sampling Rate	3 times per second
Low Battery Display	Lower 2.4V	AC Frequency Response	40-400Hz
Auto Power OFF	Approx. 30 min.	Power	F3V AAA

**Standard Accessories** : Test Leads, Holster, Manual, TP 01 Temperature Probe Bead type

**Dimension** : 185(H) x 93(W) x 35(D)mm